

R15



3  
BLADES

15 Qt.



**A SALES FEATURES**

**Vertical Cutter Mixer R15** is designed for processing both large and small quantities of meat, vegetables and smooth textured mousses, as well as for grinding and kneading food product in a minimum of time.

**B TECHNICAL FEATURES**

Vertical Cutter Mixer R15. Three-Phase. Power 4.5 HP. 2 speeds. Pulse switch. 15 Qt. stainless-steel bowl with 2 handles. Bowl-base blade assembly with 3 detachable smooth blades included. 50 to 250 meals.

Select all the options at the back page, **F** part.

**C TECHNICAL DATA**

<b>Output power</b>	4.5 HP
<b>Electrical data</b>	3-phase - Plug included
<b>Speeds</b>	1800 & 3600 rpm
<b>Dimensions (HxLxW)</b>	26 3/4" x 24 3/16" x 14 1/2" Cube: 5.46
<b>Rate of recyclability</b>	95%
<b>Net weight</b>	147 lbs
<b>Nema #</b>	L15-20P
<b>Reference</b>	R 15 - 208 - 240V/60/3

<b>D</b>	Number of meals per service	50 to 250 covers
	Working quantities per batch	12 lbs

**E PRODUCT FEATURES/BENEFITS**

**MOTOR BASE**

- Direct drive induction motor (no belt) for intensive use.
- Power 4.5 HP.
- Stainless steel motor shaft.
- Flat, easy-clean motor base.
- Magnetic safety and motor brake.
- **2 speeds : 1800 & 3600 rpm**
- Pulse function for a better cut precision.

**CUTTER FUNCTION**

- 15 Qt. stainless-steel bowl with 2 handles for a better grip.
- Central bowl locking system for easy assembly.
- Bowl-base blade assembly with 3 blades to ensure a perfectly uniform consistency, even when processing small quantity.
- Transparent lid to enable user to monitor processing.
- Opening in center of lid for adding liquid or dry ingredients during processing.

**INCLUDED ACCESSORIES**

- Stainless steel smooth blade assembly (3 blades)

**STANDARDS**

ETL electrical and sanitation Listed/ cETL (Canada)



R15

**F** OPTIONS

- Coarse serrated blade assembly (3 blades) for grinding and kneading - Ref 57098
- Fine serrated blade assembly (3 blades) for chopping herbs and spices - Ref 57099



**G** DRAWINGS & DIMENSIONS

208-240V/60/3 - delivered with cord and plug.

